Application Serial No. 09/942,939
Amdt. Dated: February 4, 2005
Reply to Office Action dated August 16, 2004

Docket No. P-0261

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently Amended) ~~In a encoding/decoding method of an RS code,~~ a-An encoding method of an RS (Reed-Solomon) code in bit level comprising ~~the steps of~~:

generating a binary equivalence matrix of the RS code by multiplying a non-binary systematic generator matrix and a binary information sequence of the RS code such that the generated binary equivalence matrix includes row and columns which are m times rows and columns of the non-binary matrix, where symbols of the non-binary matrix have a GF(2^m) dimension; and

generating row and column vectors using the binary equivalence matrix of the RS code as a component code.

2. (Currently Amended) ~~In a encoding/decoding method of an RS code,~~ a-A decoding method of [[the]] an RS (Reed-Solomon) code in bit level comprising ~~the steps of~~:

generating a̲ binary trellis using a binary parity check matrix ~~which is corresponded~~ corresponding̲ to a binary generator matrix of the RS code from a received signal; and

performing repeatedly processes of decoding ~~the~~ row and column vectors using the binary trellis and of getting extrinsic information of bit level and inputting the extrinsic information of bit level as a new decoding information,

wherein the binary generator matrix of the RS code is converted from a non-binary matrix originally representing the RS code and includes rows and columns which are m times rows and columns of the non-binary matrix, where symbols of the non-binary matrix have a $GF(2^m)$ dimension.

3.　　(Currently Amended)　~~A~~ An̲ encoding apparatus of an̲ RS (Reed-Solomon)̲ code in bit level ~~comprises~~ comprising̲:

a source information inputting unit ~~which is inputted~~ configured to receive̲ source information for encoding;

a binary conversion unit ~~being inputted~~ configured to convert̲ non-binary symbols outputted from the source information inputting unit ~~and conversing them~~ into binary symbols;

~~a~~ an̲ encoding unit ~~for encoding~~ configured to encode̲ the binary symbols ~~in order~~ to check and correct errors which may be generated by the binary symbols on a communication channel; and

Application Serial No. 09/942,939
Amdt. Dated: February 4, 2005
Reply to Office Action dated August 16, 2004

Docket No. P-0261

a modulating unit ~~for modulating~~ configured to modulate the binary symbols

encoded in the encoding unit so as to transmit the symbols through the

communication channel,

wherein the binary conversion unit generates a binary equivalence of the RS

code by multiplying a binary information sequence and a non-binary systematic

generator matrix such that the generated binary equivalence matrix includes row and

columns which are m times rows and columns of the non-binary matrix, where

symbols of the non-binary matrix have a $GF(2^m)$ dimension, and then generates a bit

level RS code using the binary equivalence matrix.

4.   (Canceled).

5.   (Original) The apparatus of claim 3, wherein the encoding unit

generates row and column vectors using the bit level RS code as a component code.

6.   (Currently Amended) A decoding apparatus of an RS (Reed-Solomon)

code in bit level comprising:

a demodulating unit ~~for demodulating the~~ configured to demodulate binary

symbols of the RS code ~~which are~~ transmitted from ~~the~~ a communication channel;

a decoding unit ~~for~~ configured to repeatedly ~~decoding the~~ decode row and

column vectors of the binary symbols using [[the]] a binary equivalence matrix of the

Application Serial No. 09/942,939
Amdt. Dated: February 4, 2005
Reply to Office Action dated August 16, 2004

Docket No. P-0261

RS code; and

a source information outputting unit ~~for outputting~~ configured to output the

decoded binary symbols as a data stream,

wherein the binary equivalence matrix of the RS code is converted from a

non-binary matrix originally representing the RS code and includes rows and columns

which are m times rows and columns of the non-binary matrix, where symbols of the

non-binary matrix have a GF(2^m) dimension.

7.   (Currently Amended) The apparatus of claim 6, wherein the decoding

unit comprises:

a column vector decoder ~~generating~~ configured to generate a column vector

by calculating the sequence of the bit level RS code and new decoding information

transmitted from the demodulating unit; and

a row vector decoder ~~generating~~ configured to generate a row vector by being

inputted the column vector transmitted from the column vector decoder, and

~~feedbacking~~ to feedback new decoding information to the column vector decoder.

8.   (New) A method of processing a Reed-Solomon (RS) code,

comprising:

transforming a non-binary matrix representation of the RS code including

non-binary symbols into a binary equivalence matrix including only binary symbols;

and

generating row and column vectors using the binary equivalence matrix.

9.   (New) The method of claim 8, wherein each non-binary symbol is transformed into an m x m matrix, where symbols of the non-binary matrix have a $GF(2^m)$ dimension.

10.   (New) The method of claim 9, wherein the binary equivalence matrix includes row and columns which are m times row and columns of the non-binary matrix.

11.   (New) The method of claim 8, further comprising:

encoding the binary symbols to check and correct errors which may be generated by the binary symbols on a communication channel; and

modulating the encoded binary symbols so as to transmit the symbols through the communication channel.

12.   (New) The method of claim 11, further comprising:

demodulating the binary symbols of the RS code transmitted from the communication channel;

repeatedly decoding row and column vectors of the binary symbols using the

Application Serial No. 09/942,939
Amdt. Dated: February 4, 2005
Reply to Office Action dated August 16, 2004

Docket No. P-0261

binary equivalence matrix of the RS code; and

outputting the decoded binary symbols as a data stream.

13.   (New) An apparatus for processing a Reed-Solomon (RS) code,

comprising:

a converting unit configured to transform a non-binary matrix representation

of the RS code including non-binary symbols into a binary equivalence matrix

including only binary symbols; and

an encoding unit configured to encode row and column vectors using the

binary equivalence matrix.

14.   (New) The apparatus of claim 13, wherein the converting unit

transforms each non-binary symbol into an m x m matrix, where symbols of the non-

binary matrix have a $GF(2^m)$ dimension.

15.   (New) The apparatus of claim 14, wherein the binary equivalence

matrix includes row and columns which are m times row and columns of the non-

binary matrix.

16.   (New) The apparatus of claim 13, further comprising:

the encoding unit configured to encode the binary symbols to check and

correct errors which may be generated by the binary symbols on a communication

channel; and

a modulating unit configured to modulate the encoded binary symbols so as to

transmit the symbols through the communication channel.

17.   (New) The apparatus of claim 16, further comprising:

a demodulating unit configured to demodulate binary symbols of the RS code

transmitted from the communication channel;

a decoding unit configured to repeatedly decode row and column vectors of

the binary symbols using the binary equivalence matrix of the RS code; and

an outputting unit configured to output the decoded binary symbols as a data

stream.